



Member State of OIML United Kingdom of Great Britain and Northern Ireland OIML Certificate No R76/2006-GB1-17.12

OIML CERTIFICATE OF CONFORMITY

NMO

Issuing authority:

Person responsible:

Mannie Panesar – Head of Technical Services

Applicant:

Thames Side Sensors Ltd. Unit 10, io Trade Centre, Deacon Way Reading, RG30 6AZ Berkshire United Kingdom

Manufacturer:

The applicant

Identification of the certified pattern:

Thames Side Sensors XT family of indicators

This certificate attests the conformity of the above-mentioned pattern (represented by the samples identified in the associated test report) with the requirements of the following Recommendation of the International Organisation of Legal Metrology (OIML):

OIML R 76 - Edition 2006(E) for accuracy class: III or IIII

This certificate relates only to the metrological and technical characteristics of the pattern of the instrument concerned, as covered by the relevant OIML International Recommendation.

This certificate does not bestow any form of legal international approval.

Important note: Apart from the mention of the certificates reference number and the name of the OIML Member State in which the certificate was issued, partial quotation of the certificate or of the associated test report is not permitted, though they may be reproduced in full.

Issue Date:

20 July 2017

Grégory Glas Technical Manager For and on behalf of the Head of Technical Services



NMO I Stanton Avenue I Teddington I TW11 OJZ I United Kingdom Tel +44 (0) 20 8943 7272 I Fax +44 (0) 20 8943 7270 I Web www.gov.uk/government/organisations/regulatory-delivery NMO is part of the Regulatory Delivery directorate within the Department for Business, Energy & Industrial Strategy The conformity was established by testing and examinations described in the associated Evaluation Report P02222 which includes 14 pages.

Characteristics of the instrument:

This Thames Side Sensors XT device, comprises a digital indicator type XT1000 and XT2000 models, is designed to be used as part of a single range, Class III or IIII, non-automatic weighing instrument. The indicators are self-indicating and DC-powered.

The instrument is not designed for direct sales to the public.

Main features:

- Stainless steel enclosure (XT1000) or plastic enclosure (XT2000)
- LED display
- Operator keypad with 5 navigation and function keys
- LED enunciators

Devices:

- Initial zero setting device on power up ($\leq 20\%$ Max)
- Semi-automatic zero setting ($\leq 4\%$ Max)
- Zero tracking (optional) ($\leq 4\%$ Max)
- Semi-automatic subtractive tare balancing (T = Max)
- Net enunciator
- Preset tare
- Zero enunciator
- Indication of stable equilibrium

Interfaces:

- Load cell connection
- RS232/485
- Analog output (optional)
- ProfiBus/ProfiNet (optional)
- EtherNet/IP (optional)

Technical data:

Power supply	10 - 28 VDC
Maximum number of scale intervals	6,000 (Class III)
Operating temperature range	- 10 °C to + 40 °C
Maximum Tare value	- Max
Load cell excitation voltage	5 VDC
Minimum load cell impedance	43 Ω
Maximum load cell impedance	1000 Ω
Minimum input voltage per verification scale	0.5 μV
interval	
Measuring range maximum voltage	+25 mV
Measuring range minimum voltage	-25 mV
Fraction of maximum permissible error	P _i = 0.5
Load cell cable (from indicator to load cell	Connect directly without junction box (4-wire
junction box) - Maximum length	configuration)
	2232 m/mm ² (6-wire configuration)

Software:

The software is held in firmware on the circuit board, and has the identification number "V1.xxxx", with xxxx reflecting non-legally relevant changes. The software version number is displayed at power-up.

Download of software and access to the legally relevant parameters is prevented by the switch located on the left-hand side of the indicator.

Software sealing may be used as an alternative: a non-editable counter designated CAL-COUNTER increments every time software is downloaded or a legally relevant parameter is changed. The value of the counter is displayed at power-up.

Sealing:

Access to the electronics is prevented by sealing the housing. This can be done by sealing the switch located on the front face, or if software sealing is used by sealing the enclosure.

CERTIFICATE HISTORY

ISSUE NO.	DATE	DESCRIPTION
R76/2006-GB1-17.12	20 July 2017	Certificate first issued.
-	-	No revisions have been issued.